

UT32M0R500 UART Flash Download

PRODUCT NAME	MANUFACTURER PART NUMBER	SMD #	DEVICE TYPE	INTERNAL PIC NUMBER
Arm Cortex M0+	UT32M0R500	5962-17212	Flash Download	QS30

1.0 Overview

This document details the process of creating and downloading a hex or srec image. Keil ARM development tools are used to create the image. Once the image is created, a Terminal Window is used to download the image via a Serial Port. For the purposes of this document, we will use the **helloworld** project from AppNote_UT32M0R500_Creating_Projects.pdf. Using this template, the user should be able to upload a hex or srec image file to Flash memory on the UT32M0R500 via UART using a Terminal Window.

2.0 Steps to Create and Download an Image to the UT32M0R500

1. Launch Keil uVision 
2. From the Project menu, select Options for Target 'Target 1'... (Figure 1).




Figure 1: Project Setup

UT32M0R500 UART Flash Download

3. In the **Options** dialog box, on the **Output** tab, check **Create HEX file** (Figure 2), and click **OK**.




Figure 2: Output Options

4. In the **Project Explorer** view, click on  and **Rebuild** the project.

UT32M0R500 UART Flash Download

- Once the hex file has been created, open **Tera Term**. From the Setup dialog box, select the correct **Port...** and set the port to the following settings (Figure 3).




Figure 3: Serial Port Settings

After you've configured the switches for BOOTCFG in the b'10 position, and hit RESET on the evaluation board, the Terminal window displays the following. (For a list of all the commands, see Figure 8 on page 10).

```
Updating from UART...

Welcome to the Cobham AES UT32M0R500 BootROM
Enter a '?' for the user menu

=>■
```

UT32M0R500 UART Flash Download

6. For this app note, we'll use image 0. The command to select the image is IMG -n#. First, we'll choose NOR Flash as the device, as in the following illustration.

```
Device to Process: DEV -t#
                   specifies target device
                   for -t (type), # can be:
                   N: for NOR Flash
                   S: for SPI Flash
                   R: for SRAM
```

```
:>DEV -tN
```

Before updating the file, choose the image number, then erase and verify it before uploading it; see below. If the error message "Embedded = 0xFFFF" is returned after VFY, it means that there is no image at the specified image; this will be resolved after the image is loaded and the CRC is calculated.

```
:>IMG -n0
```

```
NFC init SUCCESS!
```

```
:>ERS
```

```
:>VFY
```

```
ERROR: CRC mismatch. Calculated = 0x7E0C, Embedded = 0xFFFF
```

```
Image to Process:  IMG -n#
                   specifies image for next command series
                   for -n (number), # is:
                   image number: 0..3
```

UT32M0R500 UART Flash Download

7. To upload the image, use the command PGM -fH, see below.

```
:>PGM -fH
```

Now, be sure all THREE of the following features are enabled:

- a) XON/OFF software flow control
- b) 10ms line pacing
- c) binary mode

Send/upload the image (hex) file now.

```
Program Image:      PGM -f#
                    writes to-be-uploaded image
                    for -f (format), # can be:
                    H: for Intel Hex records
                    S: for Motorola S19 records
```

To load the file, first set up the Terminal with 10 msec/line "line spacing" and XON/OFF flow control (Figure 4).




Figure 4: Serial Port Upload Settings

UT32M0R500 UART Flash Download

Then, from the **File** drop-down menu, choose **Send file...** (Figure 5).




Figure 5: Send File

Open the hex file to be downloaded, and make sure Binary option is selected (Figure 6).




Figure 6: Open Hex File

UT32M0R500 UART Flash Download

As the image is being programmed to the NOR Flash, the terminal displays a line of dots as follows:

```
:>.....
```

Once programming is complete, if there are errors, the Terminal will display errors "E/1/2/3", within the line of dots. Errors are defined as follows:

'1' is for processing Intel Hex record error.

'2' is for processing Motorola S record error.

'3' is flash write record error.

Programming complete -- check progress stream for any 'E/1/2/3' (errors)
If there are no errors, the Terminal displays only the line of dots.

8. Finally verify the image by issuing VFY and CRC commands, see below.

```
:>VFY
```

```
ERROR: CRC mismatch. Calculated = 0x8C28, Embedded = 0xFFFF
```

```
:>CRC -c8C28
```

```
SUCCESS!!    CRC programmed correctly
```

```
:>VFY
```

```
SUCCESS!!    CRC match
```

```
CRC-Stamp Image:  CRC -c####
                   embeds CRC into image for verification
                   for -c <CRC>, #### MUST be:
                   four-digit hexadecimal number, all CAPS
                   (A2C4, for example)

Verify Image:     VFY
                   use embedded CRC to verify image
```

UT32M0R500 UART Flash Download

After "SUCCESS!! CRC match", change BOOTCFG to b'00 and reset or cycle power to the board. The Terminal should display "hello world" (Figure 7).




Figure 7: Hello World Display

UT32M0R500 UART Flash Download




Figure 8: Flash Download Commands

UT32M0R500 UART Flash Download

Revision History

Date	Rev. #	Author	Change Description
02/07/2019	1.0.0	JA	Initial Release

The following United States (U.S.) Department of Commerce statement shall be applicable if these commodities, technology, or software are exported from the U.S.: These commodities, technology, or software were exported from the United States in accordance with the Export Administration Regulations. Diversion contrary to U.S. law is prohibited.

Cobham Colorado Springs Inc. d/b/a Cobham Advanced Electronic Solutions (CAES) reserves the right to make changes to any products and services described herein at any time without notice. Consult an authorized sales representative to verify that the information in this data sheet is current before using this product. The company does not assume any responsibility or liability arising out of the application or use of any product or service described herein, except as expressly agreed to in writing; nor does the purchase, lease, or use of a product or service convey a license under any patent rights, copyrights, trademark rights, or any other of the intellectual rights of the company or of third parties.